

Advanced Application Field Equipment Controller (FAC) Catalog Page

LIT-1900759

2020-10-05

Advanced Application Field Equipment Controller (FAC)

The Advanced Application Field Equipment Controller (FAC) Series Controllers are programmable controllers that can communicate using BACnet/IP, MS/TP, or N2 communications protocols, depending on the model. The FAC4911 is a BACnet Advanced Application Controller (B-AAC) that communicates using BACnet/IP communications protocol. All other FAC Series controllers can be switched between MS/TP and N2 communication protocols. FAC controllers used as MS/TP devices are B-AACs with integral RS-485 MS/TP communications.

FAC Series Controllers feature an integral real-time clock. FACs support time-based tasks and maintain time-based control, which enables these field controllers to monitor and control schedules, calendars, alarms, and trends. FACs can continue time-based control and monitoring when offline for extended periods of time from a Metasys system network.

FAC Series Controllers can also operate as stand-alone controllers in applications that do not require a networked supervisory device or for network applications where it is preferred to have the scheduling, alarming, and/or trending performed locally in the field controllers.

The FAC4911 controllers operate on BACnet/IP networks and integrate into Johnson Controls® and third-party systems.



The FAC3613 model include a fast persistence feature that allows data values to be held at a configurable value, up to once per second. Persistence refers to how often samples of data are stored locally. In the event of a problem, such as a loss of power, data can be retrieved up to the rate that the data is persisted, minimizing the potential loss of data. When power is restored, previously persisted data, up to the rate of persistence, remains available and accessible. For example, if persistence is configured for once per second, you only risk losing one second of data. Persisting data may be essential for situations that require greater data accuracy, including certain methods of utility data collection and billing.

The FAC2612 controller features line-voltage relay outputs, which makes this controller well-suited for use in terminal units. The FAC2612-2 model uses a line-voltage power supply, which eliminates the need for a 24 VAC transformer in line-voltage applications.

The FAC2611, FAC2612, and FAC3613 controllers using the MS/TP protocol support wireless communications using the ZFR or ZFR Pro Series accessories and the WRZ-7860 One-to-One Receiver.

- **Important:** You cannot purchase a similar third-party device and install it in a UL/cUL Listed smoke control system. Doing so voids the UL/cUL Smoke Control Listing. Third-party devices must be provided and labeled by the factory as described in the UL/cUL Smoke Control Listing.
- **Important:** Only those Johnson Controls products identified for use in smoke control applications have been tested and listed by UL for use in a Metasys system UL 864 10th Edition UUKL/ORD-C100-13 UUKLC Smoke Control System. Installation of a product that is not UL/cUL Listed and labeled for this application prevents the entire system from being UL/cUL Listed for smoke control.

Features

Switchable Communications Protocols

Provides flexibility with a choice between BACnet MS/TP and N2 communication.

Standard BACnet Protocol

Provides interoperability with other Building Automation System (BAS) products that use the widely accepted BACnet standard.

Standard Hardware and Software Platform

Uses a common hardware design throughout the family line to support standardized wiring practices and installation workflows; also uses a common software design to support use of a single tool for control applications, commissioning, and troubleshooting to minimize technical training.

ZFR Wireless FC or SA Bus Interface

Provide a wireless alternative to hard-wired Metasys system counterparts, offering application flexibility and mobility with minimal disruption to building occupants.

Auto-Tuned Control Loops

Reduce commissioning time, eliminate change-of-season re-commissioning, and reduce wear and tear on mechanical devices.

Universal Inputs and Configurable Outputs

Allows multiple signal options to provide input/output flexibility.

BACnet Testing Laboratories (BTL) Listed and Certified

Ensures interoperability with other BTL-listed devices. BTL is a third-party agency, which validates that BAS vendor products meet the BACnet industry-standard protocol.

BACnet Automatic Discovery

Supports easy controller integration into a Metasys BAS.

End-of-Line (EOL) Switch in MS/TP Field Controllers

Enables field controllers to be terminating devices on the communications bus.

Pluggable Communications Bus and Supply Power Terminal Blocks

Expedites installation and troubleshooting.

Writable Flash Memory

Allows standard or customized applications to be downloaded from the CCT and enables persistent application data.

DIS17 Remote Display and the MAP Gateway Support

Enable monitoring and commanding of I/O and configuration parameters

Application Documentation

Refer to the *Metasys System Field Equipment Controllers and Related Products Product Bulletin (LIT-12011042)* for product application details.

FAC Series Model Information (Including Point Type Counts)

Table 1: FAC Series Model Information (Including Point Type Counts)

		FAC2513	FAC2611	FAC2612	FAC3613	FAC4911
Communication Protocol		BACnet MS/TP	BACnet MS/TP, N2			BACnet/IP
Engines Supported		All Model types. Some NIE models support MS/TP and N2 devices. Refer to the <i>Network Engines Product Bulletin (LIT-12012138)</i> for details.				SNC, SNE, OAS, NAE, and ODS at Release 9 or later.
Modular Jacks		6-pin SA Bus Modular Port supports one communicating sensor. Or you can wire up to four communicating sensors to the SA Bus Terminal Block. They cannot be used at the same time.				
		6-pin FC Bus for tool support				
Point Types	Signals Accepted					
Universal Input (UI)	Analog Input, Voltage Mode, 0–10 VDC	4 Current Mode not supported	6	5	8	10
	Analog Input, Current Mode, 4–20 mA					
	Analog Input, Resistive Mode, 0–2k ohm, RTD (1k NI [Johnson Controls], 1k PT, A99B SI), NTC (10k Type L, 2.252k Type 2)					
	Binary Input, Dry Contact Maintained Mode					

Table 1: FAC Series Model Information (Including Point Type Counts)

		FAC2513	FAC2611	FAC2612	FAC3613	FAC4911
Binary Input (BI)	Dry Contact Maintained Mode					
	Pulse Counter/ Accumulator Mode (High Speed), 100 Hz	6	2	4	6	6
Analog Output (AO)	Analog Output, Voltage Mode, 0–10 VDC	2				
	Analog Current Mode, 4–20 mA	Current Mode not supported	2		6	4
Binary Output (BO)	24 VAC Triac	2	3		6	4
Configurable Output (CO)	Analog Output, Voltage Mode, 0–10 VDC					
	Binary Output Mode, 24 VAC Triac	2	4	4		4
Relay Output (RO)	RO: Single-Pole, Double-Throw (SPDT) RO: Single-Pole, Single-Throw (SPST)			2 - SPDT and 3 - SPST line-voltage relays, 1/4 hp 120 VAC, 1/2 hp 240 VAC		

FAC Series Ordering Information

Table 2: FAC Series Ordering Information

Product Code Number	Description
MS-FAC2611-0	17-Point Advanced Application Field Equipment Controller with 6 UI, 2 BI, 4 CO, 3 BO, and 2 AO; 24 VAC; SA Bus; FC Bus; Integral Real-time Clock
MS-FAC2612-1	18-Point Advanced Application Field Equipment Controller with 5 UI, 4 BI, 4 CO, 2 SPDT and 3 SPST Line-Voltage ROs 1/4 hp 120 VAC, 1/2 hp 240 VAC; 24 VAC; SA Bus; FC Bus; Integral Real-time Clock;

Table 2: FAC Series Ordering Information

Product Code Number	Description
MS-FAC2612-2	18-Point Advanced Application Field Equipment Controller with 5 UI, 4 BI, 4 CO, 2 SPDT and 3 SPST Line-Voltage ROs, 1/4 hp 120 VAC, 1/2 hp 240 VAC; 100–240 VAC; SA Bus; FC Bus; Integral Real-time Clock
MS-FAC3613-0	26-Point Advanced Application Field Equipment Controller with 8 UI, 6 BI, 6 BO, and 6 AO; 24 VAC; SA Bus; FC Bus; Integral Real-time Clock; Fast Persistence
MS-FAC4911-0	28-Point Advanced Application Field Equipment Controller with 10 UI, 6 BI, 4 BO, 4 AO, and 4 CO; 24 VAC; SA Sensor Port; Integral Real-time Clock; 2 Ethernet Ports for BACnet/IP Communications

FAC Series Smoke Control Ordering Information

Table 3: FAC Series for Smoke Control Ordering Information

Product Code Number	Description
MS-FAC2611-0U	17-Point Advanced Application Field Equipment Controller with 6 UI, 2 BI, 3 BO, 2 AO, and 4 CO; 24 VAC, MS/TP (FC) Bus, SA Bus, integral real-time clock
MS-FAC2612-1U	18-Point Advanced Application Field Equipment Controller with 5 UI, 4 BI, 4 CO, 2 SPDR RO, and 3 SPST RO; 24 VAC, MS/TP (FC) Bus, SA Bus, integral real-time clock

- ① **Note:** These devices are UL/ULC 864 Listed, File S4977, 10th Edition UUKL/ORD-C100-13 UUKLC Smoke Control System. These devices must be ordered in a Smoke Control UUKL listing.
- ① **Note:** You cannot purchase a similar third-party device and install it in a UL/cUL Listed smoke control system. Doing so voids the UL/cUL Smoke Control Listing. Third-party devices must be provided and labeled by the factory as described in the UL/cUL Smoke Control Listing.

Accessories

- ① **Note:** The accessories marked with an asterisk (*) in the table are not qualified for use with a UL 864 UUKL/UUKLC 10th Edition Listed Smoke Control system.

Table 4: FAC Accessories

Product Code Number	Description
IOM Series Expansion Modules	Refer to the <i>Metasys System Field Equipment Controllers and Related Products Product Bulletin (LIT-12011042)</i> for a complete list of available IOM Series Expansion Modules.
TL-CCT-0	Controller Configuration Tool (CCT) software
MS-FCP-0	Metasys Field Controller Firmware Package Files for CCT
Mobile Access Portal (MAP) Gateway*	Refer to the <i>Mobile Access Portal Gateway Catalog Page (LIT-1900869)</i> to identify the appropriate product for your region.
NS Series Network Sensors	Refer to the <i>NS Series Network Sensors Product Bulletin (LIT-12011574)</i> for specific sensor model descriptions.
WRZ Series Wireless Room Sensors*	Refer to the <i>WRZ Series Wireless Room Sensors Product Bulletin (LIT-12011653)</i> for specific sensor model descriptions.
MS-DIS1710-0	Local Controller Display: Refer to <i>Local Controller Display Product Bulletin (LIT-12011273)</i> for more information.
WRZ-7860-0*	Receiver for One-to-One Wireless Room Sensing Systems - functions with WRZ Series Sensors room sensors
WRZ-SST-120*	Wireless System Survey Tool (for use with the lower power 10mW WRZ and WRZ-7860 systems)
ZFR-HPSST-0*	Wireless System Survey Tool (for use with the higher power WRG1830/ZFR183x systems)
WRG1830/ZFR183x Pro Wireless Field Bus System*	This system is used for installations that support BACnet/IP but can also coexist with the ZFR1800 Series when installed under the same supervisor such as a network engine. Refer to the <i>WRG1830/ZFR183x Pro Series Wireless Field Bus System Catalog Page (LIT-1901026)</i> for a list of available products.
Y64T15-0*	Transformer, 120/208/240 VAC Primary to 24 VAC Secondary, 92 VA, Foot Mount, 30 in. Primary Leads and 30 in. Secondary Leads, Class 2
Y65A13-0*	Transformer, 120 VAC Primary to 24 VAC Secondary, 40 VA, Foot Mount (Y65AS), 8 in. Primary Leads and 30 in. Secondary Leads, Class 2
Y65T42-0*	Transformer, 120/208/240 VAC Primary to 24 VAC Secondary, 40 VA, Hub Mount (Y65SP+), 8 in. Primary Leads and Secondary Screw Terminals, Class 2
Y65T31-0*	Transformer, 120/208/240 VAC Primary to 24 VAC Secondary, 40 VA, Foot Mount (Y65AR+), 8 in. Primary Leads and Secondary Screw Terminals, Class 2

Table 4: FAC Accessories

Product Code Number	Description
AP-TBK4SA-0	Replacement MS/TP SA Bus Terminal, 4-Position Connector, Brown (Bulk Pack of 10)
AP-TBK4FC-0	Replacement MS/TP FC Bus Terminal, 4-Position Connector (Bulk Pack of 10)
AP-TBK3PW-0	Replacement Power Terminal, 3-Position Connector, Gray (Bulk Pack of 10)
AS-CBLTSTAT-0	Cable adapter for connection to 8-pin TE-6700 Series sensors
MS-TBKLV03-0	Terminal Block Kit - FAC Line Voltage AC Power - 3 Pieces
MS-TBKRO02-0	Terminal Block Kit - FAC 2-Position Relay Output - 9 Pieces
MS-TBKRO03-0	Terminal Block Kit - FAC 3-Position Relay Output - 6 Pieces
MS-TBKCO04-0	Terminal Block Kit - FAC 4-Position Configurable Output - 6 Pieces
MS-TBKUI04-0	Terminal Block Kit - FAC 4-Position Universal Input - 3 Pieces
MS-TBKUI05-0	Terminal Block Kit - FAC 5-Position Universal Input - 3 Pieces
TL-BRTRP-0*	Portable BACnet/IP to MS/TP Router

FAC Series Technical Specifications

Table 5: FAC Series

	Description
Product Code Numbers	<p>MS-FAC2513-0: 16-Point FAC with Integral Real-Time Clock and 24 VAC Supply Power</p> <p>MS-FAC2611-0: 17-Point FAC with Integral Real-Time Clock and 24 VAC Supply Power</p> <p>MS-FAC2612-1: 18-Point FAC with Integral Real-Time Clock and 24 VAC Supply Power</p> <p>MS-FAC2612-2: 18-Point FAC with Integral Real-Time Clock and 100–240 VAC Supply Power</p> <p>MS-FAC3613-0: 26-Point FAC with Integral Real-Time Clock and 24 VAC Supply Power with Fast Persistence</p> <p>MS-FAC4911-0: 28-Point FAC with Integral Real-Time Clock and 24 VAC Supply Power; Communicates over BACnet/IP network</p> <p>Smoke Control Models:</p> <p>MS-FAC2611-0U: 17-Point FAC with Integral Real-Time Clock and 24 VAC Supply Power</p> <p>MS-FAC2612-1U: 18-Point FAC with Integral Real-Time Clock and 24 VAC Supply Power</p>
Communications Protocol	<p>MS-FAC2513-0, MS-FAC2611-0, MS-FAC2612-1, MS-FAC2612-2, and MS-FAC3613-0: BACnet MS/TP, N2</p> <p>MS-FAC4911-0: BACnet/IP</p>
Engines Supported	<p>MS-FAC2513-0, MS-FAC2611-0, MS-FAC2612-1, MS-FAC2612-2, and MS-FAC3613-0: All Model types. Some NIE models support MS/TP and N2 devices. Refer to the <i>Network Engines Product Bulletin (LIT-12012138)</i> for details.</p> <p>MS-FAC4911-0: All Model types; however, certain restrictions apply. Refer to the footnotes in the <i>Network Engine Hardware Limitations</i> table of the <i>Metasys System Configuration Guide (LIT-12011832)</i> for details.</p>
Power Requirement	<p>MS-FAC2513-0, MS-FAC2611-0, MS-FAC2612-1, MS-FAC3613-0, and MS-FAC4911-0: 24 VAC (nominal, 20 VAC minimum/30 VAC maximum), 50/60Hz, Power Supply Class 2 (North America), SELV (Europe)</p> <p>MS-FAC2612-2: 100–240 VAC 50/60 Hz</p>
Power Consumption	<p>MS-FAC2513-0, MS-FAC2611-0, MS-FAC3613-0, and MS-FAC4911-0: 14 VA maximum</p> <p>MS-FAC2612-1: 30 VA maximum</p> <p>MS-FAC2612-2: 40 VA maximum</p> <p>ⓘ Note: VA ratings do not include any power supplied to the peripheral devices connected to Binary Outputs (BOs) or Configurable Outputs (COs), which can consume up to 12 VA for each BO or CO, for a possible total consumption of an additional 84 VA (maximum).</p>
Ambient Conditions	<p>Operating: 0 to 50°C (32 to 122°F), 10 to 90% RH noncondensing; Pollution Degree 2</p> <p>Storage: -40 to 80°C (-40 to 176°F), 5 to 95% RH noncondensing</p>
Addressing	<p>For BACnet MS/TP-configured controllers: DIP switch set; valid field controller device addresses 4–127 (device addresses 0–3 and 128–255 are reserved and not valid controller addresses.)</p> <p>For BACnet/IP controllers: 3 rotary switches to assign unique number for each controller on the subnet to identify it in the Controller Tool for uploading, downloading, and commissioning</p> <p>For N2-configured controllers: DIP switch set; valid controller device addresses 1–254</p>
Communications Bus	<p>RS-485, field selectable between BACnet MS/TP and N2 communications on certain models:</p> <ul style="list-style-type: none"> • 3-wire FC Bus between the supervisory controller and field controllers • 4-wire SA Bus between field controller, network sensors, and other sensor/actuator devices, includes a lead to source 15 VDC supply power (from field controller) to bus devices. <p>MS-FAC4911-0:</p> <ul style="list-style-type: none"> • BACnet/IP over Ethernet cable • 4-wire SA Bus between field controller, network sensors, and other sensor/actuator devices, includes a lead to source 15 VDC supply power (from field controller) to bus devices.

Table 5: FAC Series

	Description
Processor	MS-FAC2611-0, MS-FAC2612-1, and MS-FAC2612-2 : H8SX/166xR Renesas® microcontroller MS-FAC2513-0 and MS-FAC3613-0 : RX631 32-Bit Renesas microcontroller MS-FAC4911-0 : RX63N 32-Bit Renesas microcontroller
Memory	MS-FAC2611-0, MS-FAC2612-1, and MS-FAC2612-2 : 4 MB Flash Memory and 1 MB RAM MS-FAC2513-0 and MS-FAC3613-0 : 16 MB Flash Memory and 8 MB SDRAM MS-FAC4911-0 : 16 MB Flash Memory and 8 MB RAM
Real-Time Clock Backup Power Supply	Super capacitor maintains power to the onboard real-time clock for a minimum of 72 hours when supply power to the controller is disconnected.
Input and Output Capabilities	MS-FAC2513-0: 4 - Universal Inputs: <i>Defined as 0–10 VDC, 0–600k ohm, or Binary Dry Contact.</i> 6 - Binary Inputs: <i>Defined as Dry Contact Maintained or Pulse Counter/Accumulator Mode.</i> 2 - Analog Outputs: <i>Defined as 0–10 VDC.</i> 2 - Binary Outputs: <i>Defined as 24 VAC Triac (external power source only)</i> 2 - Configurable Outputs: <i>Defined as 0–10 VDC or 24 VAC Triac BO</i> MS-FAC2611-0: 6 - Universal Inputs: <i>Defined as 0–10 VDC, 4–20 mA, 0–600k ohm, or Binary Dry Contact.</i> 2 - Binary Inputs: <i>Defined as Dry Contact Maintained or Pulse Counter/Accumulator Mode.</i> 2 - Analog Outputs: <i>Defined as 0–10 VDC or 4–20 mA.</i> 3 - Binary Outputs: <i>Defined as 24 VAC Triac (selectable internal or external source power).</i> 4 - Configurable Outputs: <i>Defined as 0–10 VDC or 24 VAC Triac BO.</i> MS-FAC2612-1 and MS-FAC2612-2: 5 - Universal Inputs: <i>Defined as 0–10 VDC, 4–20 mA, 0–600k ohm, or Binary Dry Contact.</i> 4 - Binary Inputs: <i>Defined as Dry Contact Maintained or Pulse Counter/Accumulator Mode.</i> 4 - Configurable Outputs: <i>Defined as 0–10 VDC or 24 VAC Triac BO.</i> 2 - Relay Outputs (Single-Pole, Double-Throw): <i>UL 916: 1/4 hp 120 VAC, 1/2 hp 240 VAC; 360 VA Pilot Duty at 120/240 VAC (B300); 3 A Non-inductive 24–240 VAC; EN 60730: 6 (4) A N.O. or N.C. only.</i> 3 - Relay Outputs (Single-Pole, Single-Throw): <i>UL 916: 1/4 hp 120 VAC, 1/2 hp 240 VAC; 360 VA Pilot Duty at 120/240 VAC (B300); 3 A Non-inductive 24–240 VAC; EN 60730: 6 (4) A N.O. or N.C. only</i> MS-FAC3613-0: 8 - Universal Inputs: <i>Defined as 0–10 VDC, 4–20 mA, 0–600k ohms, or Binary Dry Contact.</i> 6 - Binary Inputs: <i>Defined as Dry Contact Maintained or Pulse Counter/Accumulator Mode.</i> 6 - Binary Outputs: <i>Defined as 24 VAC Triac (external power source only).</i>
Input and Output Capabilities	6 - Analog Outputs: <i>Defined as 0–10 VDC or 4–20 mA</i> MS-FAC4911-0: 10 - Universal Inputs: <i>Defined as 0–10 VDC, 0–600k ohms, or Binary Dry Contact</i> 6 - Binary Inputs: <i>Defined as Dry Contact Maintained or Pulse Counter/Accumulator Mode</i> 4 - Binary Outputs: <i>Defined as 24 VAC Triac (external power source only)</i> 4 - Analog Outputs: <i>Defined as 0–10 VDC or 4–20 mA</i> 4 - Configurable Outputs: <i>Defined as AO mode , 0–10 VDC or BO mode, 24 VAC Triac</i>
Analog Input (AI)/ Analog Output (AO) Resolution and Accuracy	Analog Input: 15-bit resolution Analog Output: 15-bit resolution, +/- 200 mV accuracy in 0–10 VDC applications

Table 5: FAC Series

	Description
Terminations	<p>MS-FAC2513-0: Input/Output: Fixed Screw Terminal Blocks FC Bus, SA Bus and Supply Power: 3-wire and 4-wire Pluggable Screw Terminal Blocks SA Bus Port: RJ-12 6-pin Modular Jacks</p> <p>MS-FAC2611-0 and MS-FAC3613-0: Input/Output: Fixed Screw Terminal Blocks FC Bus, SA Bus and Supply Power: 3-wire and 4-wire Pluggable Screw Terminal Blocks FC Bus and SA Bus Port: RJ-12 6-pin Modular Jacks</p> <p>MS-FAC2612-1 and MS-FAC2612-2: Input/Output: Pluggable Screw Terminal Blocks FC Bus, SA Bus and Supply Power: 3-wire and 4-wire Pluggable Screw Terminal Blocks FC Bus and SA Bus Port: RJ-12 6-pin Modular Jacks</p> <p>MS-FAC4911-0: Input/Output: Fixed Screw Terminal Blocks SA Bus and Supply Power: 3-wire and 4-wire Pluggable Screw Terminal Blocks SA Bus Port: RJ-12 6-pin Modular Jacks</p>
Mounting	Horizontal on single 35 mm DIN rain mount (preferred), or screw mount on flat surface with three integral mounting clips on controller
Housing	Enclosure material: ABS and polycarbonate UL94 5VB, self-extinguishing; Plenum-rated Protection Class: IP20 (IEC529) (except the FAC2612 controller)
Dimensions (Height x Width x Depth)	<p>MS-FAC2513-0: 150 x 164 x 48 mm (5-7/8 x 6-7/16 x 1-7/8 in.) including terminals and mounting clips</p> <p>MS-FAC2611-0: 150 x 190 x 53 mm (5-7/8 x 7-1/2 x 2-1/8 in.) including terminals and mounting clips</p> <p>MS-FAC2612-x: 150 x 164 x 53 mm (5-7/8 x 6-7/16 x 2-1/8 in.) including terminals and mounting clips</p> <p>MS-FAC3613-0 and MS-FAC4911-0: 150 x 220 x 57.5 mm (5-7/8 x 8-3/4 x 2-3/8 in.) including terminals and mounting clips</p> <p>ⓘ Note: Mounting space for FAC models requires an additional 50 mm (2 in.) space on top, bottom, and front face of controller for easy cover removal, ventilation, and wire terminations.</p>
Weight	0.5 kg (1.1 lb)
Compliance	<p>United States: UL Listed, File E107041, CCN PAZX, UL 916, Energy Management Equipment; FCC Compliant to CFR47, Part 15, Subpart B, Class A UL Listed, File S4977, UL 864 UUKL/UUKLC 10th Edition Listed, Smoke Control Units and Accessories for Fire Alarm Systems Equipment (models with U product code suffix only)</p> <p>Canada: UL Listed, File E107041, CCN PAZX7, CAN/CSA C22.2 No. 205, Signal Equipment; Industry Canada Compliant, ICES-003 UL Listed, File S4977, UL 864 UUKL/ORD-C100-13 10th Edition Listed, Smoke Control Units and Accessories for Fire Alarm Systems (models with U product code suffix only)</p> <p>Europe: CE Mark – Johnson Controls declares that this product is in compliance with the essential requirements and other relevant provisions of the EMC Directive and RoHS Directive. Johnson Controls, declares that the FAC2612-2 models are also in compliance with the essential requirements and other relevant provisions of the Low Voltage Directive. Declared as Independently Mounted, Intended for Panel Mounting, Operating Control Type 1.B, 4kV rated impulse voltage, 100°C ball pressure test.</p> <p>Australia and New Zealand: RCM Mark, Australia/NZ Emissions Compliant</p> <p>BACnet International: MS-FAC261x-x: BACnet® Testing Laboratories (BTL) Protocol Revision 7 Listed BACnet Advanced Application Controller (B-AAC) MS-FAC2513-0, MS-FAC3613-0, and MS-FAC4911-0: BACnet® Testing Laboratories (BTL) Protocol Revision 18 Listed and Certified BACnet Advanced Application Controller (B-AAC)</p>